



Use and maintenance instructions

Erica (FBT version)


Outdoor luminaire suitable for installation on wall or ceiling

TECHNICAL DETAILS: refer to the product label

 The UE declaration of conformity can be downloaded from our website www.marecoluce.it


 Insulation Class II

IP65 Protection degree against dust ingress, solid particles, moisture

 This product must not be disposed as a normal household waste

WARNINGS:

- THE SAFETY OF THIS PRODUCT IS GUARANTEED ONLY WITH THE RESPECT OF THE EXISTING RULES FOR THE ELECTRICAL SYSTEMS, AND WITH THE APPROPRIATE USE OF THESE INSTALLATION INSTRUCTIONS, THEREFORE IT IS NECESSARY TO KEEP THEM.
- THE IMPROPER USE OF THIS PRODUCT IS FORBIDDEN; ANY TAMPERING WITH THE PRODUCT OR MODIFICATION OF THE PRODUCT THAT IS NOT AUTHORIZED BY MARECO LUCE CAN CAUSE DAMAGE TO PEOPLE, ANIMALS OR THINGS, AND WILL VOID ANY WARRANTY OR LIABILITY.
- SWITCH OFF THE ELECTRICITY BEFORE CONDUCTING ANY KIND OF MAINTENANCE.
- THE PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH BEST PRACTICE.
- IN CASE OF DAMAGED COMPONENTS, THEY MUST BE REPLACED WITH SPARE PARTS SUPPLIED BY MARECO LUCE BEFORE SWITCHING ON THE LUMINAIRE.
- THE LUMINAIRE CAN BE INSTALLED THROUGH THE USE OF A CABLE DUCT. PAY ATTENTION: IN THIS CASE IT IS NOT POSSIBLE TO KEEP THE IP RATE DECLARED.
- MAX LAMP SIZE (IN MM): 15W D60 L140



GENERAL MAINTENANCE RECOMMENDATIONS:

- CLEAN THE LUMINAIRE PERIODICALLY IN ORDER TO REMOVE DIRT DEPOSITS ON THE DIFFUSER.
- CHECK THE TIGHTENING OF THE FIXING SCREWS TO THE INSTALLATION SURFACE, AND THE TIGHTENING OF THE CLOSING SCREWS OF THE LUMINAIRE.
- DO NOT USE HARSH DETERGENTS TO CLEAN THE DIFFUSER.
- CHECK THE INTEGRITY OF THE FITTING COMPONENTS: REPLACE THEM IN CASE OF DAMAGE BY USING ONLY ORIGINAL MARECO LUCE PARTS.
- CHECK THE GASKETS THAT MUST NOT BE HARDENED, BROKEN OR IN ANY WAY DAMAGED.
- DO NOT REMOVE OR TAMPER WITH THE GROMMET TO NOT COMPROMISE THE IP RATE OF THE LUMINAIRE.

INSTALLATION INSTRUCTIONS:

1. Unhook the closing clips (1) and remove the diffuser (2).
2. Unscrew the screws (3) and remove the lamp-holder protection (4).
3. Insert each single conductor of the power supply cable (5) into the grommet (6);
- ATTENTION:** use only a power cable with a maximum section of 0.75mmq;
4. Secure the luminaire to the wall or ceiling by using some screws and expansion caps (not included);
- ATTENTION:** Choose screws and expansion caps suitable for the type of installation that you are conducting.
5. Insert the rubber caps (7) (supplied) in the fixing seats, in order to keep the IP rate declared.
6. Connect the single conductors to the terminals of the lamp holder (8) paying attention to respect the polarities.
7. Reposition the lamp holder protection (4) and tighten the screws (3).
8. Insert the lamp (not included).
9. Position the diffuser (2) and hook it with the clips (1).

FOR INSTALLATION WITH THE USE OF CABLE DUCT:

- a. Unhook the closing clips (1) and remove the diffuser (2).
- b. Open the pre-drilled inlet of the cable duct (9) placed on the edge of the luminaire by using a suitable tool.
- c. Unscrew the screws (3) and remove the lamp-holder protection (4).
- d. Continue from point 4 of these installation instructions.

