



The company Mareco Luce S.R.L., as manufacturer of lighting fittings, hereby declares, under its own responsibility, that the products below are in conformity to the following EEC directives, changes included and with the relevant national standards

2014/30/UE	EMC Directive, updates 92/31/EEC and 93/68/EEC
2014/35/UE	Low Voltage Directive
2011/65/CE	Directive on the restriction of the use of hazardous substances in EEA
2009/125/CE	Energy related products

and declares to have applied the following Standards and technical specifications, or parts of them:

IEC 62778:2014	Application of IEC 62471 for the assessment of blue light hazard to light sources and luminaires
EN 62471:2008	Photobiological safety of lamps and lamp systems
EN 62493:2015	Assessment of lighting equipment related to human exposure to electromagnetic fields
EN 61547:2009	EMC for immunity
EN 50581:2012	Technical documentation for the assessment of the electrical and electronic product with respect to the restriction of hazardous substances
EN 60598-1:2015	Lighting fittings - Part 1: General Prescriptions and tests
EN 55015:2013	Limits and methods of measurement of radio disturbances characteristics of electrical lighting and similar equipment.
EN 61000-3-2:2014	Electromagnetic Compatibility (EMC). – Part 3: Limits Section 2: Limits for harmonic current emissions (equipment input current of 16 A per phase).
EN 61000-3-3:2013	Electromagnetic Compatibility (EMC). - Part3: Limits Section 3: limitation of voltage fluctuation and flicker in low-voltage supply systems for equipment with rated current of 16 A.
EN 60598-2-1	Lighting Fittings – Part 2: Particular requirements Fixed general purpose luminaires
EN 60598-2-22	Lighting Fittings – Part 2: Particular requirements Luminaires for emergency lighting

Item code	Electrical data
026029A_	FAST MAX LED 21,7W 4000K EMERGENCY
026029R_	FAST MAX LED 21,7W 4000K EMERGENCY + MOTION SENSOR
026029U_	FAST MAX LED 21,7W 3000K EMERGENCY + MOTION SENSOR
026029Z_	FAST MAX LED 21,7W 3000K EMERGENCY
026127A_	FAST MAX LED 21,7W 4000K MOTION SENSOR
026127B_	FAST MAX LED 21,7W 3000K MOTION SENSOR
0261282_	FAST MAX LED 30W 4000K
0261284_	FAST MAX LED 30W 3000K
026129A_	FAST MAX LED 21,7W 4000K EMERGENCY
026229A_	FAST MAX PLUS LED 21.7W 4000K EMERGENCY
026229R_	FAST MAX PLUS LED 21,7W 4000K EMERGENCY + MOTION SENSOR



MARECO LUCE s.r.l

Via S.Croce 121 (z.i.)
47032 Bertinoro (FC)
Tel. +39 0543 4687
Fax +39 0543 449051
info@marecoluce.it
export@marecoluce.it
P.I./C.F. IT 02156430403
R.I. 18235 – R.E.A. 246017



026229U_	FAST MAX PLUS LED 21,7W 3000K EMERGENCY + MOTION SENSOR
026229Z_	FAST MAX PLUS LED 21,7W 3000K EMERGENCY
026327A_	FAST MAX PLUS LED 4000K MOTION SENSOR
026327B_	FAST MAX PLUS LED 3000K MOTION SENSOR
0263282_	FAST MAX PLUS LED 4000K
0263284_	FAST MAX PLUS LED 3000K

Bertinoro (FC), 14/06/2018

MARECO LUCE S.R.L.
Ufficio Tecnico

Mondardini Ing. Luigi



MARECO LUCE s.r.l

Via S.Croce 121 (z.i.)
47032 Bertinoro (FC)
Tel. +39 0543 4687
Fax +39 0543 449051
info@marecoluce.it
export@marecoluce.it
P.I./C.F. IT 02156430403
R.I. 18235 – R.E.A. 246017