47032 bertinoro (FC) Italia
via s.croce, 121 (z.i.)
tel. +39 0543 4687
fax +39 0543 449051
info@marecoluce.it
www.marecoluce.it

This document is exclusive MARECO LUCE s.r.l., is strictly prohibited disclosure or reproduction, even partial, as well the use of without written consent of MARECO LUCE s.r.l..The company reserves the right to change models, dimensions and materials at any time without notice.

PRODUCT DATA SHEET
Edge 60° surge protection Kit
Code : CS160037

- When purchased the protection kit will be installed inside the fitting
- These protective components are fitted with an LED indicator
- Once the end of the component's life has been reached, the green LED goes out and the protective component has to be replaced
- If the protective luminaire component overloads, the connected lighting circuit will be interrupted

TECHNICAL SPECS
- AC-system: TT-TN-IT
- Temporary overvoltage:
(TOV)-LV: 443VCA (5sec.) /443V (120min.)
(TOV)-MV/HV: 1200VCA (200 msec.)
- Isccr: 4500A
- With integrated thermal fuse
- DEKRA approved acc. to IEC 61643-11
- Class II
- Screw terminals: 0,75-2,5 mm²
- Protection degree: IP67
- Max impulse voltage: UOC 10KV
- Voltage protection level: L-N <1500V

Rev. 1 - 06/03/20

Details
• Conformity with EU Directives
• IP

